# **LED Lamp E14**



6 SMD LED / Direct voltage





Reference : <u>E14-360-30V-6J-HT</u>

Bulb base — Viewing angle — Voltage — Number of LED — Color — Température resistance

#### **Generalities**

The LED lamps «E14» with 6 high brightness SMD LED and a wide angle light, in direct voltage, are mainly used for signaling devices, Lighting signals, night lights or Lighting for a reduced volume. Electrical connections are made on rear lamp base. Kind base: E14 lamp screw.

## **Description**

- Base : Lamp base E14, galvanized steel. RoHS compliant.
- Colors: Available in yellow (J) (580nm) and red (R) (630nm), other colors on request.
- Linghting: 6 SMD LED (surface mounted device) high brightness.
- $\geq$  6000mcd &  $\geq$  140lm in yellow and  $\geq$  6000mcd &  $\geq$  110lm in red.

### **Technical specifications**

Supply voltages and consumptions :

Voltages	rating voltage U = 24Vdc	Admissible supply voltages U = from 16 to 30Vdc
Red (R) Yellow Amber (J)	test condition = 24Vdc; Ta=25°C Current I = 62mA +/- 10mA Power P = 1.4 W +/- 0.2W	

- Conformities: CEI 60061-1 (7004-23), ROHS, CE.
- Lifetime (MTBF\*): 50 000 hours.
- Operating temperature : -40°C à +55°C.
- IP protection standard : not available.

(\* : mean time between failure)










# **Advantages**

- •Insensitivity to vibrations, mechanical shocks.
- •Immunity against magnetic fields.
- · Assembly and disassembly easy, fast and secure .
- •Incredible long life and low heat dissipation.


#### Connections

#### Screw lamp base E14



Connections in 2 possible sens.


1: «+» if 2 is connected on «-»
2: «-» if 1 is connected on «+»
and conversely



**Electrical symbol** 

# **Mechanical specifications**

• Fixing : Screw lamp base E14. Sizes +/- 0.5mm.



#### /Working





• On :













#### **Options & warranty**

- **Options :** On request, other voltages, other colors and other LED number.
- **Warranty :** 12 months manufacturer. No terminal or steel part must be welded or lose the guarantee.
- **Recommendation :** Using a stand or adapter to receive the types of lamp bases F14.

